


Current Sensor

Product Series: STK-HO-Z

Part number: STK-150HO-Z
STK-180HO-Z
STK-200HO-Z
STK-250HO-Z
STK-300HO-Z

Version: Ver1.8



CONTENT

1.	Summary.....	2
2.	STK-150HO-Z Electrical performance.....	4
3.	STK-180HO-Z Electrical performance.....	5
4.	STK-200HO-Z Electrical performance.....	6
5.	STK-250HO-Z Electrical performance.....	7
6.	STK-300HO-Z Electrical performance.....	8
7.	Output voltage VS primary current.....	9
8.	Maximum continues DC current.....	11
9.	Frequency response and bandwidth.....	12
10.	Step response time.....	12
11.	Frequency delay performance.....	13
12.	Dimension & Pin definitions.....	14
13.	Appendix: typical application circuit.....	15

1. Summary

The STK-H0-Z series is based on open-loop technology and design. It is suitable for DC, AC, pulse and any type of irregular current measurement under isolated conditions. The nominal current range of STK-H0-Z current sensors includes 150 A, 180 A, 200 A, 250 A, 300A.

Typical applications

- PV combiner box
- PV inverter (MPPT & AC)
- motor driver controller
- SMPS & UPS
- Battery management system

Standards

- EN50178:1997
- IEC 61010-1:2010
- IEC 61326-1:2012

General parameter

Parameter	Symbol	Unit	Value
Working temperature	T_A	°C	-40 ~ 105
Storage temperature	T_stg	°C	-40 ~ 105
Mass	m	g	23.6

Absolute maximum rating

Parameter	Symbol	Unit	Value
Supply voltage (non-destructive)	V _C	V	6.0
ESD rating (HBM)	U _{ESD}	kV	4
ESD rating (CDM)	U _{CDM}	kV	1.5

Remark: the unrecoverable damage may occur when the product works on the conditions over the absolute maximum ratings. Long-time working on the absolute maximum ratings may cause the degradation on performance and reliability.

Ratings

Parameter	Symbol	Unit	Value
Primary involved potential		V AC/DC	600
Ambient operating temperature	T_A	°C	105
Primary current	I_p	A	According to series primary current
Secondary supply voltage	U_c	V DC	5
Output voltage	V_out	V	0.1 ~ 4.9

Isolation parameter

Parameter	Symbol	Unit	Value	Comment
RMS voltage for AC test 50Hz/1 min	U _d	kV	5	
Impulse withstand voltage 1.2/50μs	Ū _w	kV	8	
Clearance distance (pri. -sec)	dCl	mm	11	Shortest distance through air
Creepage distance (pri. -sec)	dCp	mm	11	Shortest path along device body
Comparative tracking index	CTI	V	600	
Case material			V0 according to UL 94	
Application example		V	600	Reinforced insulation, CAT III, PD 2, non uniform field according EN 50178, IEC 61010
Application example		V	1000	Basic insulation, CAT III, PD 2, non uniform field according EN 50178, IEC 61010
Application example		V	1500	Basic insulation, CAT III, PD 2, according to IEC 62109-1 Altitude ≤ 3000 m
Application example		V	600	CAT III, PD 2, according to UL 508

2. STK-150HO-Z Electrical performance

 Condition: $T_A = 25^\circ\text{C}$ $V_{cc} = 5\text{ V}$ (Except special instructions)

Parameter	Symbol	Unit	Min	Typ	Max	Comment
Primary nominal current rms	I _{pn}	A		150		
Primary current measuring range	I _{pm}	A	-375		375	
Supply voltage	V _{cc}	V	4.75	5	5.25	
Current consumption	I _{cc}	mA		8	10	
Reference voltage	V _{ref}	V	2.48	2.5	2.52	Output function
Rated output voltage	V _{FS}	V		0.8		(V _{out} - V _{ref})@ I _{pn}
Internal output resistance	R _{out}	Ω		1		Output
Quiescent voltage	V _{off}	V	2.48	2.5	2.52	V _{out} @ 0 A
Electrical offset voltage	V _{oe}	mV	-5		5	T _A @ 25°C
Magnetic offset current	I _{om}	A	-0.75		0.75	@ ±10 x I _{pn}
Theoretical gain	G _{th}	mV/A		5.333		800mV @ I _{pn}
Error of gain	Err _G	%G _{th}		±1		Trimmed in the factory @ 25°C
Temperature drift of gain	G _{TR}	%G _{th}	-1.0		1.0	-40°C ~ 105°C
Temperature drift of V _{oe}	V _{oe} _TRange	%V _{FS}	-1.5		1.5	-40°C ~ 105°C
Rated linearity error	Non-L _{pn}	%I _{pn}	-0.5		0.5	±I _{pn}
Linearity error @ I _{pm}	Non-L _{pm}	%I _{pm}	-3		3	±I _{pm}
Reaction time	t _{ra}	μs			1	@ 10% of I _{pn}
Step response time	t _{res}	μs		0.3	1	@ 90% of I _{pn}
Delay time	t _{delay}	μs			1	300 kHz sine wave
Frequency bandwidth (-3dB)	BW	kHz		300		No RC circuit
Output voltage noise DC ~ 10 kHz DC ~ 100 kHz	V _{noise}	mVpp		10 15		
Accuracy @ 25°C	X	% of I _{pn}	-1		1	@ 25°C
Accuracy @ -40°C ~ 105°C ①	X _{TRange}	% of I _{pn}	-2		2	-40°C ~ 105°C

Remarks:

 ①. the accuracy @ -40°C~105°C, $X_{TRange} = (((V_{out} - V_{ref})@ I_n @ T_x) - V_{oe}@ 25^\circ\text{C} - G_{th} * I_n) / V_{FS}$, where T_x represents present temperature, G_{th} is fitted gain at room temperature .

3. STK-180HO-Z Electrical performance

Condition: $T_A = 25^\circ\text{C}$ $V_{cc} = 5\text{ V}$ (Except special instructions)

Parameter	Symbol	Unit	Min	Typ	Max	Comment
Primary nominal current rms	I _{pn}	A		180		
Primary current measuring range	I _{pm}	A	-450		450	
Supply voltage	V _{cc}	V	4.75	5	5.25	
Current consumption	I _{cc}	mA		8	10	
Reference voltage	V _{ref}	V	2.48	2.5	2.52	Output function
Rated output voltage	V _{FS}	V		0.8		(V _{out} - V _{ref})@ I _{pn}
Internal output resistance	R _{out}	Ω		1		Output
Quiescent voltage	V _{off}	V	2.48	2.5	2.52	V _{out} @ 0 A
Electrical offset voltage	V _{oe}	mV	-5		5	T _A @ 25°C
Magnetic offset current	I _{om}	A	-0.9		0.9	@ ±10 x I _{pn}
Theoretical gain	G _{th}	mV/A		4.444		800mV @ I _{pn}
Error of gain	Err _G	%G _{th}		±1		Trimmed in the factory @ 25°C
Temperature drift of gain	G _{TR}	%G _{th}	-1.0		1.0	-40°C ~ 105°C
Temperature drift of V _{oe}	V _{oe} _TRange	%V _{FS}	-1.5		1.5	-40°C ~ 105°C
Rated linearity error	Non-L _{pn}	%I _{pn}	-0.5		0.5	±I _{pn}
Linearity error @ I _{pm}	Non-L _{pm}	%I _{pm}	-3		3	±I _{pm}
Reaction time	t _{ra}	μs			1	@ 10% of I _{pn}
Step response time	t _{res}	μs		0.3	1	@ 90% of I _{pn}
Delay time	t _{delay}	μs			1	300 kHz sine wave
Frequency bandwidth (-3dB)	BW	kHz		300		No RC circuit
Output voltage noise DC ~ 10 kHz DC ~ 100 kHz	V _{noise}	mVpp		10 15		
Accuracy @ 25°C	X	% of I _{pn}	-1		1	@ 25°C
Accuracy @ -40°C ~ 105°C ①	X _{TRange}	% of I _{pn}	-2		2	-40°C ~ 105°C

Remarks:

①. the accuracy @ -40°C~105°C, $X_{TRange} = (((V_{out} - V_{ref})@ I_n @ T_x) - V_{oe}@ 25^\circ\text{C} - G_{th} * I_n) / V_{FS}$, where T_x represents present temperature, G_{th} is fitted gain at room temperature .

4. STK-200HO-Z Electrical performance

 Condition: $T_A = 25^\circ\text{C}$ $V_{cc} = 5\text{V}$ (Except special instructions)

Parameter	Symbol	Unit	Min	Typ	Max	Comment
Primary nominal current rms	I _{pn}	A		200		
Primary current measuring range	I _{pm}	A	-500		500	
Supply voltage	V _{cc}	V	4.75	5	5.25	
Current consumption	I _{cc}	mA		8	10	
Reference voltage	V _{ref}	V	2.48	2.5	2.52	Output function
Rated output voltage	V _{FS}	V		0.8		(V _{out} - V _{ref}) @ I _{pn}
Internal output resistance	R _{out}	Ω		1		Output
Quiescent voltage	V _{off}	V	2.48	2.5	2.52	V _{out} @ 0 A
Electrical offset voltage	V _{oe}	mV	-5		5	T _A @ 25°C
Magnetic offset current	I _{om}	A	-1		1	@ ±10 x I _{pn}
Theoretical gain	G _{th}	mV/A		4		800mV @ I _{pn}
Error of gain	Err _G	%G _{th}		±1		Trimmed in the factory @ 25°C
Temperature drift of gain	G _{TR}	%G _{th}	-1.0		1.0	-40°C ~ 105°C
Temperature drift of V _{oe}	V _{oe} _TRange	%V _{FS}	-1.5		1.5	-40°C ~ 105°C
Rated linearity error	Non-L _{pn}	%I _{pn}	-0.5		0.5	±I _{pn}
Linearity error @ I _{pm}	Non-L _{pm}	%I _{pm}	-3		3	±I _{pm}
Reaction time	t _{ra}	μs			1	@ 10% of I _{pn}
Step response time	t _{res}	μs		0.3	1	@ 90% of I _{pn}
Delay time	t _{delay}	μs			1	300 kHz sine wave
Frequency bandwidth (-3dB)	BW	kHz		300		No RC circuit
Output voltage noise DC ~ 10 kHz DC ~ 100 kHz	V _{noise}	mVpp		10 15		
Accuracy @ 25°C	X	% of I _{pn}	-1		1	@ 25°C
Accuracy @ -40°C ~ 105°C ①	X _{TRange}	% of I _{pn}	-2		2	-40°C ~ 105°C

Remarks:

 ①. the accuracy @ -40°C~105°C, $X_{TRange} = (((V_{out} - V_{ref}) @ I_n @ T_x) - V_{oe} @ 25^\circ\text{C} - G_{th} * I_n) / V_{FS}$, where T_x represents present temperature, G_{th} is fitted gain at room temperature .

5. STK-250HO-Z Electrical performance

 Condition: $T_A = 25^\circ\text{C}$ $V_{cc} = 5\text{ V}$ (Except special instructions)

Parameter	Symbol	Unit	Min	Typ	Max	Comment
Primary nominal current rms	I _{pn}	A		250		
Primary current measuring range	I _{pm}	A	-625		625	
Supply voltage	V _{cc}	V	4.75	5	5.25	
Current consumption	I _{cc}	mA		8	10	
Reference voltage	V _{ref}	V	2.48	2.5	2.52	Output function
Rated output voltage	V _{FS}	V		0.8		(V _{out} - V _{ref})@ I _{pn}
Internal output resistance	R _{out}	Ω		1		Output
Quiescent voltage	V _{off}	V	2.48	2.5	2.52	V _{out} @ 0 A
Electrical offset voltage	V _{oe}	mV	-5		5	T _A @ 25°C
Magnetic offset current	I _{om}	A	-1.25		1.25	@ ±10 x I _{pn}
Theoretical gain	G _{th}	mV/A		3.2		800 mV @ I _{pn}
Error of gain	Err _G	%G _{th}		±1		Trimmed in the factory @ 25°C
Temperature drift of gain	G _{TR}	%G _{th}	-1.0		1.0	-40°C ~ 105°C
Temperature drift of V _{oe}	V _{oe} _TRange	%V _{FS}	-1.5		1.5	-40°C ~ 105°C
Rated linearity error	Non-L _{pn}	%I _{pn}	-0.5		0.5	±I _{pn}
Linearity error @ I _{pm}	Non-L _{pm}	%I _{pm}	-3		3	±I _{pm}
Reaction time	t _{ra}	μs			1	@ 10% of I _{pn}
Step response time	t _{res}	μs		0.3	1	@ 90% of I _{pn}
Delay time	t _{delay}	μs			1	300 kHz sine wave
Frequency bandwidth (-3dB)	BW	kHz		300		No RC circuit
Output voltage noise DC ~ 10 kHz DC ~ 100 kHz	V _{noise}	mVpp		10 15		
Accuracy @ 25°C	X	% of I _{pn}	-1		1	@ 25°C
Accuracy @ -40°C ~ 105°C ①	X _{TRange}	% of I _{pn}	-2		2	-40°C ~ 105°C

Remarks:

 ①. the accuracy @ -40°C~105°C, $X_{TRange} = (((V_{out} - V_{ref})@ I_n @ T_x) - V_{oe}@ 25^\circ\text{C} - G_{th} * I_n) / V_{FS}$, where T_x represents present temperature, G_{th} is fitted gain at room temperature .

6. STK-300HO-Z Electrical performance


Condition: $T_A = 25^\circ\text{C}$ $V_{cc} = 5\text{ V}$ (Except special instructions)

Parameter	Symbol	Unit	Min	Typ	Max	Comment
Primary nominal current rms	I _{pn}	A		300		
Primary current measuring range	I _{pm}	A	-700		700	
Supply voltage	V _{cc}	V	4.75	5	5.25	
Current consumption	I _{cc}	mA		8	10	
Reference voltage	V _{ref}	V	2.48	2.5	2.52	Output function
Rated output voltage	V _{FS}	V		0.8		(V _{out} - V _{ref})@ I _{pn}
Internal output resistance	R _{out}	Ω		1		Output
Quiescent voltage	V _{off}	V	2.48	2.5	2.52	V _{out} @ 0 A
Electrical offset voltage	V _{oe}	mV	-5		5	T _A @ 25°C
Magnetic offset current	I _{om}	A	-1.5		1.5	@ ±10 x I _{pn}
Theoretical gain	G _{th}	mV/A		2.6667		800 mV @ I _{pn}
Error of gain	Err _G	%G _{th}		±1		Trimmed in the factory @ 25°C
Temperature drift of gain	G _{TR}	%G _{th}	-1.0		1.0	-40°C ~ 105°C
Temperature drift of V _{oe}	V _{oe} _TRange	%V _{FS}	-1.5		1.5	-40°C ~ 105°C
Rated linearity error	Non-L _{pn}	%I _{pn}	-0.5		0.5	±I _{pn}
Linearity error @ I _{pm}	Non-L _{pm}	%I _{pm}	-3		3	±I _{pm}
Reaction time	t _{ra}	μs			1	@ 10% of I _{pn}
Step response time	t _{res}	μs		0.3	1	@ 90% of I _{pn}
Delay time	t _{delay}	μs			1	300 kHz sine wave
Frequency bandwidth (-3dB)	BW	kHz		300		No RC circuit
Output voltage noise DC ~ 10 kHz DC ~ 100 kHz	V _{noise}	mVpp		10 15		
Accuracy @ 25°C	X	% of I _{pn}	-1		1	@ 25°C
Accuracy @ -40°C ~ 105°C ①	X _{TRange}	% of I _{pn}	-2		2	-40°C ~ 105°C


Remarks:

①. the accuracy @ -40°C~105°C, X_{TRange} = (((V_{out} - V_{ref})@ I_n @ T_x) - V_{oe}@ 25°C - G_{th} * I_n) / V_{FS}, where T_x represents present temperature, G_{th} is fitted gain at room temperature .


7. Output voltage VS primary current




The dependence of Vout of STK-150HO-Z on the primary current.




The dependence of Vout of STK-180HO-Z on the primary current.



The dependence of V_{out} of STK-200HO-Z on the primary current.




The dependence of V_{out} of STK-250HO-Z on the primary current.




The dependence of Vout of STK-300HO-Z on the primary current.

8. Maximum continues DC current




The dependence of maximum continues current of STK-xxHO-Z current on the working temperature.

9. Frequency response and bandwidth




The frequency bandwidth of STK-xxHO-Z series current sensor. The bandwidth of current sensor is DC ~ 300 kHz (-3dB).

10. Step response time







The typical frequency response of STK-xxHO-Z current sensor. The response time from 90% of the primary current (red) to 90% of the secondary output (blue) is less than 1 µs.

11. Frequency delay performance




When testing 300 kHz sine wave, the typical result of STK-xxHO-Z current sensor's output. The response time from the primary current (red) to the secondary output (blue) is less than 1 μ s.

12. Dimension & Pin definitions




Terminal Pin Identification:


- 1 : Vcc
- 2 : GND
- 3 : Vout
- 4 : Vref (OUT)
- 5 : NC
- 6, 7, 8: Primary input Current (+)
- 9, 10, 11: Primary input Current (-)




Recommended PCB Layout:



Material : Fit UL94V-0 & RoHS requirements ;
General tolerance : ±0.5
Unit :mm



13. Appendix: typical application circuit



Typical application circuits for STK-H0-Z current sensor. The magnification can be estimated as $M = R4/R2$ with the condition of $R1 = R2$, and $R3 = R4$, $C3 = C4$. The magnification in the above circuit is about 3, The signal input to ADC is $1.65 + R4/R2 * (Vout - Vref)$.

R3 (kohm)	C3 (pF)	Theoretical -3dB $f = 1/(2\pi RC)$ (kHz)	Measured -3dB (kHz)
10	47	398	~340
20	81	98	~ 100
20	810	10	~ 10

The frequency characteristics of STK-H0-Z series current sensor are not affected by the R-C setting (according to recommended R-C setting), therefore the active filter circuit or R-C circuit can be applied to modulate the sensor's frequency characteristics.